

Coaxial Band-stop Filter

Stopband: 3300-3800MHz

Model: TLRF-3300M-3800M-E

TLRF-3300M-3800M-E is a coaxial band-stop filter with a stop band frequency from 3300 to 3800MHz and a pass band frequency from DC to 3100MHz and 4000 to 6500MHz. The maximum insertion loss of the filter is 3 dB and the minimum rejection is 50 dB.

Features:

- Stopband Frequency Range 3100 to 3800MHz
- Lower Cost
- High Rejection

Applications:

- Communicatin Systems
- Radar Systems
- Sub-assemblies

Electrical Characteristics:

Parameter	Min	Typ	Max	Units
Stopband Frequency rang	3100		3800	MHz
Passband Frequency range	DC-3100 & 4000-6500			MHz
Stopband Rejection	50			dB
Passband Insertion Loss			3	dB
Passband VSWR			1.8	:1
Power Handling			5	W
Impedance		50		Ohms

Envrionmental And Physical Characteristics:

Description	Parameter	Units
Operating Temperature	-20 to +60	°C
Input /Output Connector	SMA Female/SMA Female	
Size		mm

Outline Drawing:

Unit:mm



ESD Protection: Strictly
adhere to ESD precautions
to prevent electrostatic
damage.

Ordering Information:

Base Number	Description	Revision
TLRF-3300M-3800M-E	Coaxial Band-stop Filter,Stopband: 3300-3800MHz,Passband: DC-3100MHz&4000-6500MHz, Stopband rejection:50dB Min	Rev.1.0