

Coaxial Band-pass Filter

2.396-2. 408GHz/ SMA Female

Model: TBF-2402-12

TBF-2402-12 is a coaxial band-pass filter with a passband frequency from 2.396 to 2.408GHz and a rejection frequencies at 2.382GHz and at 2.422GHz. The nominal insertion loss of the filter is 2.5dB and the typical rejection is 40 dB.

Features:

- Passband Frequency Range 2.396 to 2.408GHz
- Low Insertion Loss
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations


电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	单位 Units
通带频率范围 Passband Frequency range	2.396		2.408	GHz
通带插损 Passband Insertion Loss			2.5	dB
带内纹波 Pass Band Ripple			2.3	dB
带外抑制 Rejection	>40dB@fo±20Mhz			dB
耐受功率 Power Handling			15	W
输入驻波 Input VSWR			1.5	:1
输出驻波 Output VSWR			1.5	:1
阻抗 Impedance	50			Ohms

环境和机械特性 Envirionmental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
操作温度 Operating Temerature	-40 To +70	℃
存储温度 Storage Temerature	-40 to +70	℃
接口 Connectors	SMA Female	

外形图Outline Drawing: Unit:mm;



ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TBF-2402-12	Coaxial Band-pass Filter, Passband frequency range: 2.396 to 2.408GHz, Passband Insertion Loss: 2.5dB, SMA Female	Rev.1.0

典型曲线 Typical Performance Data:



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.