

Coaxial Band-pass Filter

3.5-4.1GHz/ SMA Female

Model: TLBF-3G8-600M-E

TLBF-3G8-600M-E is a coaxial band-pass filter with a passband frequency from 3.5 to 4.1GHz and a rejection frequencies at 2.8 and 4.6 GHz. The nominal insertion loss of the filter is 1.2 dB and the typical rejection is 70 dB.

Features:

- Passband Frequency Range: 3.5 to 4.1GHz
- Low Insertion Loss
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations


电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	Units
通带频率范围 Passband Frequency range	3.5		4.1	GHz
通带插损 Passband Insertion Loss			1.2	dB
带内纹波 Pass Band Ripple			0.4	dB
带外抑制 Rejection	>70dB@DC-2.8GHz 4.6GHz			dB
耐受功率 Power Handling			15	W
输入驻波 Input VSWR			1.3	:1
输出驻波 Output VSWR			1.3	:1
阻抗 Impedance	50			Ohms

环境和机械特性 Envirionmental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
操作温度 Operating Temerature	-40 To +70	℃
存储温度 Storage Temerature	-40 to +70	℃
接口 Connectors	SMA Female	

外形图Outline Drawing: Unit:mm;




ESD Protection: Strictly
adhere to ESD precautions
to prevent electrostatic
damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TLBF-3G8-600M-E	Coaxial Band-pass Filter, Passband frequency range: 3.5 to 4.1GHz, Passband Insertion Loss: 1.2dB, SMA Female	Rev.1.0

典型曲线 Typical Performance Data:



Note: Above data is for ref only, actual data may vary from unit to unit depending on operating environment and other factors like material lots etc.