

Coaxial Band-pass Filter

3.3-3.8GHz/ SMA Female

Model: TLBF-3G55-500M-E

TLBF-3G55-500M-E is a coaxial band-pass filter with a passband frequency from 3.3 to 3.8GHz and a rejection frequencies at 2.9GHz and 4.2 GHz. The nominal insertion loss of the filter is 1.0dB and the typical rejection is 70 dB.

Features:

- Passband Frequency Range 3.3 to 3.8GHz
- Low Insertion Loss
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations


电气特性 Electrical Characteristics:

参数 Parameter	Min	Typ	Max	单位 Units
通带频率范围 Passband Frequency range	3.3		3.8	GHz
通带插损 Insertion Loss			1.0	dB
带内纹波 Pass Band Ripple			0.8	dB
带外抑制 Rejection	>70dB@2.9Ghz >60dB@4.2Ghz(2次谐波)			dB
耐受功率 Power Handling			50	W
输入驻波 Input VSWR			1.5	:1
输出驻波 Output VSWR			1.5	:1
阻抗 Impedance	50			Ohms

环境和机械特性 Envirionmental And Physical Characteristics:

类型 Description	参数 Parameter	单位 Units
操作温度 Operating Temperature	-40 To +70	℃
存储温度 Storage Temperature	-40 to +70	℃
接口 Connectors	SMA Female	

外形图 Outline Drawing: Unit:mm;



ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

订货信息 Ordering Information:

标准型号 Base Number	描述 Description	版本号 Revision
TLBF-3G55-500M-E	Coaxial Band-pass Filter, Passband frequency range: 3.3 to 3.8GHz, Passband Insertion Loss: 1.0dB, SMA Female	Rev.1.0