

Coaxial Band-pass Filter

17.2-17.4 GHz/SMA Female

Model: TLBF-17G3-200M-E

TLBF-17G3-200M-E is a coaxial band-pass filter with a passband frequency from 17.2 to 17.4 GHz and a rejection frequencies from 16.75 GHz to 17.85 GHz. The maximum insertion loss of the filter is 1.8 dB and the typical rejection is 50 dB.

Features:

- Passband Frequency Range 17.2 to 17.4 GHz
- Low Insertion Loss
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations

电气特性 Electrical Characteristics:


Parameter	Min	Typ	Max	Units
Passband Frequency range	17.2		17.4	GHz
Band Width			200	MHz
Insertion Loss			1.8	dB
Pass Band Ripple			1.0	dB
Rejection	>50dB@fC±450MHz			dB
Power Handling			50	W
VSWR			1.6	:1
Impedance	50			Ohms

Envrionmental And Physical Characteristics:

Description	Parameter	Units
Operating Temerature	-40 To +70	°C
Connectors	SMA Female	

Outline Drawing:

Unit:mm



ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:

Base Number	Description	Revision
TLBF-17G3-200M-E	Coaxial Band-pass Filter, Passband frequency range: 17.2-17.4GHz, Passband Insertion Loss: 1.8dB, SMA Female	Rev.1.0