

Coaxial Band-pass Filter

Center Frequency 625 MHz/SMA Female

Model: TLBF-625M-10M-L

TLBF-625M-10M-L is a coaxial band-pass filter with a passband center frequency at 625 MHz and a rejection frequencies point at 600 MHz and 650 MHz. The maximum insertion loss of the filter is 3.0 dB and the minimum rejection is 50 dB.

Features:

- Passband Center Frequency 625 MHz
- High Rejection
- Steep Rejection Skirts

Applications:

- Instrumentations
- Radar Systems
- System Integrations

Electrical Characteristics:


Parameter	Min	Typ	Max	Units
Passband Frequency range	620		630	MHz
Band Width			10	MHz
Passband Insertion Loss			3.0	dB
Pass Band Ripple			2.8	dB
VSWR			1.6	:1
Rejection@600MHz&650MHz	50			dB
Power Handling			3	W
Impedance	50			Ohms

Envrionmental And Physical Characteristics:

Description	Parameter	Units
Operating Temerature	-40 To +70	°C
Connectors	SMA Female	
Size	10*12*40.4	mm

Outline Drawing:

Unit:mm



ESD Protection: Strictly adhere to ESD precautions to prevent electrostatic damage.

Ordering Information:

Base Number	Description	Revision
TLBF-625M-10M-L	Coaxial Band-pass Filter, Passband center frequency: 625MHz, Passband Insertion Loss: 3.0dB, SMA Female	Rev.1.0